

Dificuldade na configuração do PPPOE.



Acesse a ONU via interface gráfica, com o IP 192.168.1.1 e com o usuário e senha na qual descrita debaixo da ONU, e após acessar vá em:

ADMIN > ONU DEVICE TYPE

e selecione o modo HGU MODE.

O modo HGU libera as configurações de PPPOE no dispositivo ONU.



Após selecionar HGU mode, clique em Apply Changes.
Após isto o dispositivo ONU irá reiniciar e retornara com as Opções de WAN
Acesse novamente a ONU via interface gráfica, com o IP 192.168.1.1 e com o usuário e senha na qual descrita debaixo da ONU, e após acessar vá em:

WAN > PON WAN

The screenshot displays the 'PON WAN' configuration page in the ShoreLine SH901R web interface. The page title is 'PON WAN' and it includes a 'Logout' button in the top right corner. The main content area is titled 'This page is used to configure the parameters for PONWAN'. The configuration fields are as follows:

- nas0_0** (dropdown menu)
- WanName:** Cdai
- Enable VLAN:**
- VLAN ID:** 2003
- 802.Ip_Mark:** 0 (dropdown menu)
- Channel Mode:** PPPoE (dropdown menu)
- Enable NAPT:**
- Admin Status:** Enable Disable
- Connection Type:** INTERNET (dropdown menu)
- MTU:** 1492
- Enable IGMP Proxy:**
- IP Protocol:** IPv4/IPv6 (dropdown menu)
- PPP Settings:**
 - Username:** aleuzasantos
 - Password:** [masked]
 - Type:** Continuous (dropdown menu)
 - Idle Time (sec):** [empty]
 - Authentication Method:** AUTO (dropdown menu)
 - AC-Name:** [empty]
 - Service-Name:** [empty]
- IPv6 WAN Setting:**
 - Address Mode:** Slaac Static
 - Enable DHCPv6 Client:**
 - Request Options:**
 - Request Address
 - Request Prefix
- Port Mapping:**
 - LAN_1

At the bottom of the page, there are two buttons: 'Apply Changes' and 'Delete'.

Exemplo Básico de configuração de rede PPPOE.